

Product Code: DPAB595BK

Luckinslive 438820917

Description: 13A Ingot 1 Gang Switched Socket Outlet With Twin Type C USB (4.2A) Outlets



General Information

Dimensions (mm)	91 (W) x 91 (H) x 28 (D)	
Plate Dimensions (mm)	88 (W) x 88 (H) x 8 (D)	
Dimensions With Gasket (mm)	91 (W) x 91 (H) x 9 (D)	
Plate Fixing Centres - Horizontal (mm)	60.3	
Style	Rounded Profile	
Finish	Antique Brass	
Insert Colour	Black	
Gasket Colour	Black	
Materials	Front Plate: Stainless Steel Housing: Nylon Terminals: Brass Contacts: Silver "on-lay" Copper / Brass PCB: Mixed Components	Insert: Urea Switch Cover: Stainless Steel Terminal Screws: Steel & Yellow Passivated Internal Busbars: Formed Pressed Brass Earth Strap: Mild Steel
Anti Microbial Certified	No	
Operating Voltage (AC)	250	Frequency (Hz) 50
Resistive Load Rating (A)	13	
USB Output Type	USB Type 'C'	USB Charging Total Load (A) 4.2
USB Number Of Outputs	2	USB Standby Current (W) 0.1
USB Charging Voltage (V DC)	5	
Termination Type	Screw	Terminal Torque Value (Nm) 1.2
Terminal Size (mm)	Ø5	
Terminal Capacity - Solid (mm ²)	3 x 2.5 or 2 x 4	
Single Pole Switched	Yes	
3 Pin Safety Shuttered	Yes	
Product Marking	5V DC 4.2A (SHARED)	
Minimum Back Box Depth (mm)	25	
Ingress Protection	IP20	
Operational Temperature (°C)	-5 to +40	
Warranty (Years)	20	Warranty - Electronics (Years) 2
Standards	BS 1363-2: 2016 +A1: 2018, EN IEC 62368-1, EN IEC 62368-3, EN IEC 62680-1-3, EN IEC 61000-6-1 & EN 61000-6-3	

Additional Information

For cleaning / polishing of products, use only a soft, dry, clean cloth.

The USB circuits within this socket outlet are designed to withstand insulation resistance tests at 500V.

Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product.

Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.

Independent Charging: 5V DC, 4.2A – USB Type C (3A), USB Type C (3A)

Intelligent chip incorporated within the USB PCB adjusts the output according to the load connected.