

Product Code: MCP053

Luckinslive 437625812

Description: 13A Fused Connection Unit With LED & Optional Flex Outlet



### General Information

Dimensions (mm)	88 (W) x 88 (H) x 48 (D)	
Plate Fixing Centres - Horizontal (mm)	60.3	
Style	Metal Clad Pro	
Colour	Dusty Grey	
Insert Colour	Polar White	
Materials	Insert, Switch, Fuse Drawer & Housing: Urea	LED Lens: Polycarbonate
	Terminals: Brass	Terminal Screws: Steel & Yellow Passivated
	Contacts: Silver "on-lay" Copper / Brass	Internal Busbars: Formed Pressed Brass
	Earth Strap: Mild Steel	
Operating Voltage (AC)	250	Frequency (Hz) 50
Resistive Load Rating (A)	13	
Fuse Fitted Type	Plug Top Cartridge Fuse	
Termination Type	Screw	
Terminal Size (mm)	4.8 x 4.8	Terminal Torque Value (Nm) 1.2
Terminal Capacity - Solid (mm <sup>2</sup> )	3 x 2.5 or 2 x 4	
Switched	No	
Twin Earth Terminals	Yes	
LED Indicator	Yes	Indicator Colour Red
Flex Outlet Available	Yes	
Flex Outlet Location	Front of Plate	Flex Outlet Dimension (mm) Ø10
Supplied Back Box Depth (mm)	40	
Back Box Knockouts - Total (mm)	6 x Ø20	
Back Box Knockouts - Top (mm)	1 x Ø20	Back Box Knockouts - Bottom (mm) 1 x Ø20
Back Box Knockouts - Left Side (mm)	2 x Ø20	Back Box Knockouts - Right Side (mm) 1 x Ø20
Back Box Knockouts - Rear (mm)	1 x Ø20	
Back Box Earth Terminal Supplied	Yes	
Ingress Protection	IP20	
Operational Temperature (°C)	-5 to +40	
Warranty (Years)	20	

**Standards** BS 1363-4, BS 1362

### Additional Information

For cleaning / polishing of products, use only a soft, dry, clean cloth.

LED Indicators are not designed to withstand insulation resistance testing at 500V. Carrying out insulation resistance testing at 500V may result in damage to the LED indicator. Please disconnect prior to insulation resistance testing.

Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product.

Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.

