

Product Code: CSP043

Luckinslive 422559854

Description: 10A 1 Gang Smart Switching Receiver



General Information

Materials	Housing: Polycarbonate	Electronics: PCB & Electronic Components
Operating Voltage (AC)	220-240	Frequency (Hz) 50/60
Load Rating (W)	250 (2300)	
Load Rating Comments	LED (Resistive)	
Termination Type	Screw	
Terminal Size (mm)	3 x 2	Terminal Torque Value (Nm) 0.2
Terminal Capacity - Solid (mm²)	3 x 1.5	
Protocol	Zigbee	Signal Transmission Frequency 2.400 to 2.484GHz
Open Air Wireless Range (M)	<100	
Standby Current (mA)	1	
Working Current (mA)	10	
Indicator Colour	Green	
Minimum Back Box Depth (mm)	35 (47 Flat Plate)	
Ingress Protection	IP20	
Working Humidity	10%-90%RH	
Operational Temperature (°C)	-10 to +40	
Warranty (Years)	3	

Standards BS EN 60669-2-1, BS EN 55035, BS EN 61000-3-2, BS EN 61000-3-3, BS EN 62311

Additional Information

Neutral connection required
Zigbee signal mesh
Utilises standard 230V switch wiring with permanent live & neutral required
Voice control via ClickSmart+ Hub using Alexa and/or Google Home

Components Supplied Switching Receiver, Mounting Bracket (DIN Rail Mountable or Screw Fixable), Instruction Manual

Installation Overview Neutral connection required
Utilises standard on/off switches
Can be multi-way switch controlled along with control via the ClickSmart+ app

Programming Information With hub and app setup and receiver wired and powered, if not in pairing mode press the switch 'On' and 'Off' five times, the receiver LED will start flashing or the switch 'On' and 'Off' no longer operates to confirm in pairing mode. Can be paired with hub via app.

