

Product Code: DPSC595GY

Luckinslive 438821424

Description: 13A Ingot 1 Gang Switched Socket Outlet With Twin Type C USB (4.2A) Outlets



General Information

Dimensions (mm)	g1 (W) x g1 (H) x 28 (D)		
Plate Dimensions (mm)	88 (W) x 88 (H) x 8 (D)		
Dimensions With Gasket (mm)	g1 (W) x g1 (H) x g (D)		
Plate Fixing Centres - Horizontal (mm)	60.3		
Style	Rounded Profile		
Finish	Satin Chrome		
Insert Colour	Grey		
Gasket Colour	Grey		
Materials	Front Plate: Stainless Steel		Insert: Urea
	Housing: Nylon		Switch Cover: Stainless Steel
	Terminals: Brass		Terminal Screws: Steel & Yellow Passivated
	Contacts: Silver "on-lay" Copper / Brass		Internal Busbars: Formed Pressed Brass
	PCB: Mixed Components		Earth Strap: Mild Steel
Anti Microbial Certified	No		
Operating Voltage (AC)	250		
Resistive Load Rating (A)	13		
USB Output Type	USB Type 'C'		
USB Number Of Outputs	2		
USB Charging Voltage (V DC)	5		
Termination Type	Screw		
Terminal Size (mm)	Ø5		
Terminal Capacity - Solid (mm²)	3 x 2.5 or 2 x 4		
Single Pole Switched	Yes		
3 Pin Safety Shuttered	Yes		
Product Marking	5V DC 4.2A (SHARED)		
Minimum Back Box Depth (mm)	25		
Ingress Protection	IP20		
Operational Temperature (°C)	-5 to +40		
Warranty (Years)	20		
Standards	BS 1363-2: 2016 +A1: 2018, EN IEC 62368-1, EN IEC 62368-3, EN IEC 62680-1-3, EN IEC 61000-6-1 & EN 61000-6-3		Frequency (Hz) 50
			USB Charging Total Load (A) 4.2
		USB Standby Current (W) 0.1	
		Terminal Torque Value (Nm) 1.2	
		Warranty - Electronics (Years) 2	

Additional Information

For cleaning / polishing of products, use only a soft, dry, clean cloth.
The USB circuits within this socket outlet are designed to withstand insulation resistance tests at 500V.
Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product.
Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.
Independent Charging: 5V DC, 4.2A – USB Type C (3A), USB Type C (3A)
Intelligent chip incorporated within the USB PCB adjusts the output according to the load connected.

