

Product Code: B1AKIT
Description: Assist Call Kit



Component 1 Description
B1APCM – Pull Cord Module

Quantity
1

Component 2 Description
B1AM – Alert Module

Quantity
1

General Information	
Dimensions (mm)	86 x 86 x 22
Finish	Brushed Steel
Materials	Stainless Steel & Polycarbonate
Mounting	Surface or Flush
Weight (Kg)	0.6
Supply & Power	
Cable Size (mm²)	1 - 1.5
Connection Type	1 x 2 Core Radial
Programming	
Adjustment Type	Pull Cord
Communication	
Maximum Communication Range (m)	500 (point to point)
Inputs & Outputs	
Input Lines	1
Alarm Zone End of Line (Resistance)(Ω)	10k
Line Outputs	Single Line
Environment	
Storage Temperature (°C)	

General Information	
Dimensions (mm)	86 x 86 x 22
Finish	Brushed Steel
Materials	Stainless Steel & Polycarbonate
Mounting	Surface or Flush
Indication	Blue ‘Halo’
Cable Size (mm²)	1 - 1.5
Connection Type	1 x 2 Core Radial
Maximum Communication Range (m)	500 (point to point)
Input Lines	1
Alarm Zone End of Line (Resistance)(Ω)	10k
Line Outputs	Single Line
Weight (Kg)	0.6

Component 3 Description

B1ACM – Pull Cord Cancel Module

Quantity
1

General Information	
Dimensions (mm)	86 x 86 x 22
Finish	Brushed Steel
Materials	Stainless Steel & Polycarbonate
Mounting	Surface or Flush
Indication	Blue ‘Halo’
Cable Size (mm²)	1 - 1.5
Connection Type	1 x 2 Core Radial
Adjustment Type	Single Cancel Button
Maximum Communication Range (m)	500 (point to point)
Input Lines	1
Alarm Zone End of Line (Resistance)(Ω)	10k
Line Outputs	Single Line
Weight (Kg)	0.6

Warranty Years 2

Additional Information The kit requires the B1A4ZM (Assistance Alarm 4 Zone Module) or Beacon Master Station to operate

Unit 7 Target Park, Shawbank Road,
Lakeside, Redditch B98 8YN United Kingdom
T: +44 (0)1527 515150 | F: +44 (0)1527 515143
E: info@espuk.com | W: espuk.com



CLICK OR SCAN

Catalogue



DoC



Installation



CLICK OR SCAN